



LYRIC^{VoIP}

Asterisk configuration note

Sip.conf

```
[Lyric]
type=friend
host=10.0.100.224
fromdomain=10.0.100.224
fromuser=lyric
username=lyric
secret=4321
dtmfmode=rfc2833
disallow=all
allow=ulaw
allow=alaw
```

Extension.conf

```
[outbound_cell]
exten => _09XXXXXXXX,1,Dial(SIP/Lyric/${EXTEN:2})
```

The screenshot shows the Asterisk configuration interface for Lyric VoIP, divided into two main sections: 'CHAMADAS PBX A LYRIC (SIP A GSM)' and 'CHAMADAS LYRIC A PBX (GSM A SIP)'. The first section includes a 'Porta' field set to 5060, a yellow warning box about accepting calls from any IP, and checkboxes for 'Limitar segundo endereço IP' (unchecked), 'Pedir autenticação' (checked), 'Usuário' (lyric), and 'Senha' (masked). The second section includes 'Chamadas entrantes' set to 'ATIVADO/RETORNO [CONFIGURAR]', 'Endereço IP PBX' (192.168.200.108), 'Porta' (5060), 'Autenticar em PBX' (checked), 'Usuário' (lyric), 'Senha' (masked), 'Discar a ramal' (checked), 'Ramal' (100), 'Enviar caller ID estendido' (checked), 'Caller ID' (Gateway Lyric), and 'Incluir' checkboxes for 'IMSI' and 'Operadora celular' (both checked).